

Features

- · Since it has a frequency deviding function, it is able to obtain a frequency devision of 1/2-1/28 (1/256)
- · The symmetry of frequency devided output is within 50±2%
- · The oscillation start time has the fast starting characteristic of being 1.5msec.or less
- The pin arrangement is DIP 8PIN
- Supply voltage VDD=5.0V

Applications

Amusement

How to Order

KCEXO3- 20.0000 C 5 1 B 00 $\overline{}$ $\overline{}$ $\overline{}$ $\overline{}$ $\overline{}$ $\overline{}$ $\overline{}$ $\overline{}$ 2


- ①Type
- 2 Output Frequency
- 3 Output Type (CMOS)
- 4 Supply Voltage (5.0V)
- ⑤Frequency Tolerance
- ⑥Symmetry/EnableFunction (40/60%, Stand-by)
- **⑦Customer Special Model Suffix** (STD Specification is "00")

Specifications


lto	Symbol	Conditions	Specifications		Unita
Item			Min.	Max.	Units
Output Frequency Range	F ₀		11.0592	24.576	MHz
Frequency Tolerance (Overall)	F_tol		-100	+100	×10 ⁻⁶
Storage Temperature Range	T_stg		-40	+85	°C
Operating Temperature Range	T_use		-10	+70	°C
Supply Voltage	V _{DD}		4.5	5.5	V
Current Consumption	loo		-	20	mA
Symmetry	SYM	@50% VDD	40	60	%
Rise / Fall Time	Tr/Tf		-	15	nS
Output Voltage-"L"	Vol		-	10% V _{DD}	V
Output Voltage-"H"	Vон		90% V _{DD}	_	V
Output Load	CL		-	50	pF
Start-up Time	ST		-	1.5	mS

Note: All electrical characteristics are defined at the maximum load and operating temperature range. Please contact us for inquires about operating temperature range, available frequencies and other conditions.

Dimensions



Settings of the frequency devision output



- Outputs the original frequency (fo) of 1.F
- the internal quartz crystal.

 Outputs the frequency of programmed 2.D
- dividing ratio $(fo/2^n)$. Possible to be oscillated when set to 3.ST HIGH level and stopped in oscillation when set to LOW level. when this function is not needed, be sure to set the STANDBY pin to the HIGH level.

4.GND

- 6.B 7.C Used to program the dividing ratio for the original frequency. Supply voltage
- 8.V_{DD}

Pin connection

Input				Output			
Select			ST	F	D Divided		
С	В	Α	31	Original Frequency	Wave form		
L	L	L	Н	fo clock	fo · 1/2 clock		
L	L	Н	Н	fo clock	fo · 1/2² clock		
L	Н	L	Н	fo clock	fo · 1/2³ clock		
L	Н	Н	Н	fo clock	fo · 1/24 clock		
Н	L	L	Н	fo clock	fo · 1/2 ⁵ clock		
Н	L	Н	Н	fo clock	fo · 1/26 clock		
Н	Н	L	Н	fo clock	fo · 1/2 ⁷ clock		
Н	Н	Н	Н	fo clock	fo · 1/2 ^s clock		
_	_	_	L	L	L		